



# 10 Bay Android and iPad SYNC & CHARGE Cabinet

- With Combination Lock

### Part no. SB-M10G2



Reprogrammable Combination Lock



Slide-in door to save space




Sync Functionality up to 10 Devices











### **Adjustable Shelves**

Adjustable shelves to fit in a variety of tablets. Built-in with cable management features.

8 Shelves:

6 Shelves: 10 Shelves: 242(H) x 52(W) x 280(D)mm 242(H) x 28(W) x 280(D)mm 242(H) x 37(W) x 280(D)mm





## Slide-in Door

Slide-in doors saves spaces and allows you to use the cabinet in tighter spaces.

Door Length Fully 320mm Expanded:

Door Length Fully 105mm Retracted:



Physical Characteristic	s
External Dimensions (mm	) 430(H) × 400(W) × 350(D)mm
Slot Dimensions (mm)	6 Shelves: 242(H) x 52(W) x 280(D)mm; 8 Shelves: 242(H) x 37(W) x 280(D)mm; 10 Shelves: 242(H) x 28(W) x 280(D)mm
Weight	N.W. 15.6 kgs G.W: 18 kgs
Fan	DC12V / 0.11A / 6x6mm
Power	
Input	AC220~240V, 50/60Hz, 2A
Output	DC 5V, 2.4A from each USB port

### Capacity

10 devices Via 10 USB Ports DC 5V, 2.4A from each USB port

#### Package Includes

Charging Cabinet x 1, User Manual x 1, Power Cord x 1

#### Warranty

10 years on the Chassis, 2 years on the electrical components